

Вива-Телеком. Распиновка разъема Motorola PMLN5072

	D-	USB / APM Ground	APM 1 (1-wire)	Power Ground	Spkr+	Audio Ground	Rx Audio	Ground	Ground	GP5_6	GP5_7	GP5_8	VIP_1 (Ext Alarm)
	2	4	6	8	10	12	14	16	18	20	22	24	26
	1	3	5	7	9	11	13	15	17	19	21	23	25
D+	Vbus	APM 2 (1-wire)	SW B+	Spkr-	Tx Audio	Aux Audio Out 1 / RxD	Aux Audio Out 2 / TxD	GP5_1 (PTT)	GP5_2 (Monitor)	GP5_3 (Chan Act)	Emerg Sw	Ign Sense	